

# Magnetic Contactor Selection Table

## Overhead Traveling Crane Use

### 3 Phase 380V~440V 50Hz/60Hz

No.	Rated Motor Power kW	Rated Motor Current A	Contactor Model
1	0.75	2.1	S-PA6
2	1.1	2.9	S-PA9
3	2.2	4.6	S-PA9
4	3	7	S-P11
5	3.7	8.6	S-P11
6	4	9	S-P16
7	5.5	12	S-P25
8	7.5	15	S-P35T
9	9	18	S-P40T
10	11	21	S-P60T
11	15	27	S-P100T
12	18.5	35	S-P125T
13	22	40	S-P150T
14	30	52	S-P200T
15	37	65	S-P220T
16	45	75	S-P220T
17	55	100	S-P300T
18	65	115	S-P300T
19	75	130	S-P400T

### 3 Phase, 200V~230V, 50Hz/60Hz

No.	Rated Motor Power kW	Rated Motor Current A	Contactor Model
1	0.3	1.7	S-PA6
2	0.37	2.1	S-PA6
3	0.55	2.8	S-PA9
4	0.75	3.6	S-PA9
5	1.1	4.6	S-PA9
6	1.5	7	S-P11
7	2.2	9	S-P16
8	3	12	S-P30T
9	4	16	S-P40T
10	5.5	24	S-P50T
11	7.5	30	S-P80T
12	9	35	S-P100T
13	11	44	S-P150T
14	15	58	S-P200T
15	18.5	65	S-P220T
16	22	85	S-P300T
17	30	105	S-P300T
18	37	135	S-P400T



**Shihlin Electric**

All Rights Reserved

Breaker & Switchgears Oversea Sales Dept.

3F, No.9, Sec. 1, Chang-An E. Rd., Taipei City, Taiwan

Tel: +886-2-2541-9822 Fax: +886-2-2581-2665

e-mail: [b.export@seec.com.tw](mailto:b.export@seec.com.tw)

<http://circuit-breaker.seec.com.tw>